

TCS 455: Quiz 4

Semester/Year: 2/2009

Course Title: Mobile Communications

Name	ID

Instructions

1. Separate into groups of no more than three persons.
2. Closed book. Closed notes.
3. Only one submission is needed for each group. Late submission will not be accepted.
4. **Do not panic.**

Use the fact below to construct **Hadamard Matrix H_8** .

If N is a power of two and $H_1 = [0]$. Then H_{2N} can be found as follows:

$$H_{2N} = \begin{bmatrix} H_N & H_N \\ H_N & \overline{H_N} \end{bmatrix}$$

where $\overline{H_N}$ is the complement of H_N .

Caution: You answer will be a matrix with 0s and 1s.

$$H_2 = \begin{bmatrix} H_1 & H_1 \\ H_1 & \overline{H_1} \end{bmatrix} = \begin{bmatrix} 0 & 0 \\ 0 & 1 \end{bmatrix}$$

$$H_4 = H_{2 \times 2} = \begin{bmatrix} H_2 & H_2 \\ H_2 & \overline{H_2} \end{bmatrix} = \begin{bmatrix} 0 & 0 & 0 & 0 \\ 0 & 1 & 0 & 1 \\ 0 & 0 & 1 & 1 \\ 0 & 1 & 1 & 0 \end{bmatrix}$$

$$H_8 = H_{2 \times 4} = \begin{bmatrix} H_4 & H_4 \\ H_4 & \overline{H_4} \end{bmatrix} = \begin{bmatrix} 0 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 1 & 0 & 1 & 0 & 1 & 0 & 1 \\ 0 & 0 & 1 & 1 & 0 & 0 & 1 & 1 \\ 0 & 1 & 1 & 0 & 0 & 1 & 1 & 0 \\ 0 & 0 & 0 & 0 & 1 & 1 & 1 & 1 \\ 0 & 1 & 0 & 1 & 1 & 0 & 1 & 0 \\ 0 & 0 & 1 & 1 & 1 & 1 & 0 & 0 \\ 0 & 1 & 1 & 0 & 1 & 0 & 0 & 1 \end{bmatrix}$$