HW 1 — Due: Feb 5

Lecturer: Asst. Prof. Dr. Prapun Suksompong

Instructions

- (a) Must solve all non-optional problems. (5 pt)
 - (i) Write your first name and the last three digit of your student ID on the upper-right corner of *every* submitted page.
 - (ii) For each part, write your explanation/derivation and answer in the space provided.
- (b) ONE part of a question will be graded (5 pt). Of course, you do not know which part will be selected; so you should work on all of them.
- (c) Late submission will be rejected.
- (d) Write down all the steps that you have done to obtain your answers. You may not get full credit even when your answer is correct without showing how you get your answer.

Problem 1 (HW1-2015-2). Consider the code $\{0, 01\}$

- (a) Is it nonsingular?
- (b) Is it uniquely decodable?

(c) Is it prefix-free?

$$S_X = \{x_1, x_2, \dots, x_7\}.$$

Their corresponding probabilities are given by

		x_1		-		-		
p_{\perp}	X(x)	0.49	0.26	0.12	0.04	0.04	0.03	0.02

(a) Find the entropy H(X).

(b) Find a binary Huffman code for X.

(c) Find the expected codelength for the encoding in part (b).

Problem 3 (HW1-2015-2). Find the entropy and the binary Huffman code for the random variable X with pmf

$$p_X(x) = \begin{cases} \frac{x}{21}, & x = 1, 2, \dots, 6, \\ 0, & \text{otherwise.} \end{cases}$$

Also calculate $\mathbb{E}\left[\ell(X)\right]$ when Huffman code is used.

Problem 4 (HW1-2015-2). These codes cannot be Huffman codes. Why?

- (a) $\{00, 01, 10, 110\}$
- (b) $\{01, 10\}$
- (c) $\{0,01\}$

Problem 5 (HW1-2015-2). A memoryless source emits two possible message Y(es) and N(o) with probability 0.9 and 0.1, respectively.

- (a) Determine the entropy (per source symbol) of this source.
- (b) Find the expected codeword length per symbol of the Huffman binary code for the third-order extensions of this source.

- (c) Use MATLAB to find the expected codeword length **per (source) symbol** of the Huffman binary code for the fourth-order extensions of this source.
 - (i) Put your answer here.
 - (ii) Don't forget to attach the **printout** of your MALTAB script (highlighting the modified parts if you start from the provided class example) and the expression-s/results displayed in the command window.
- (d) Use MATLAB to plot the expected codeword length **per (source) symbol** of the Huffman binary code for the *n*th-order extensions of this source for n = 1, 2, ..., 8. Attach the **printout** of your plot.

Problem 6 (HW1-2015-2). (Optional) The following claim is sometimes found in the literature:

"It can be shown that the length $\ell(x)$ of the Huffman code of a symbol x with probability $p_X(x)$ is always less than or equal to $\left[-\log_2 p_X(x)\right]$ ".

Even though it is correct in many cases, this claim is not true in general.

Find an example where the length $\ell(x)$ of the Huffman code of a symbol x is greater than $\left[-\log_2 p_X(x)\right]$.

Hint: Consider a pmf that has the following four probability values $\{0.01, 0.30, 0.34, 0.35\}$.

Problem 7 (HW1-2015-2). (Optional) Construct a random variable X (by specifying its pmf) whose corresponding Huffman code is $\{0, 10, 11\}$.